

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Correction to number of subcarriers per subchannel for 2048-FFT (PUSC)	
Date Submitted	2006-09-27	
Source(s)	Prince Arora NEC Technologies (UK) Ltd. Nader Zein NEC	Voice: +44 (0) 118 9654566 Fax: +44 (0) 118 9257191 mailto:prince.arora@nectech.co.uk Voice +44 (0) 2087523863 Fax: +44 (0) 2087523861 mailto:nader.zein@ttd.neceur.com
Re:		
Abstract	Correction to number of subcarriers per subchannel for 2048-FFT (PUSC)	
Purpose	The contribution is to correct the number of subcarriers per subchannel for 2048-FFT uplink subcarrier allocations in case of PUSC.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Correction to number of subcarriers per subchannel for FFT-2048 (PUSC)

Prince Arora & Nader Zein

Introduction

This contribution is to correct the number of subcarriers per subchannel for FFT 2048 in case of PUSC. The proposed changes reflects the correct number of subcarriers per subchannel in the OFDMA uplink subcarrier allocation table and specify the permutation used.

Detailed Text Changes

Modify text in section 8.4.6.2

The uplink supports 70 subchannels for PUSC permutation, and 96 subchannels for optional PUSC permutation. Each In PUSC allocation, transmission uses 48 data carriers as the minimal block of processing. Each new transmission for the uplink commences with the parameters as given in Table 313 for PUSC permutation, and with the parameters as given in Table 315 for optional PUSC permutation.

Modify Table 313.

Table 313 – 2048-FFT OFDMA uplink subcarrier allocations for PUSC

Parameter	Value	Notes
Number of dc subcarriers	1	<u>Index 1024</u>
Nused	1681	<u>Number of all subcarriers used within a symbol</u>
Guard subcarriers: Left, Right	184, 183	=
TilePermutation	6, 48, 58, 57, 50, 1, 13, 26, 46, 44, 30, 3, 27, 53, 22, 18, 61, 7, 55, 36, 45, 37, 52, 15, 40, 2, 20, 4, 34, 31, 10, 5, 41, 9, 69, 63, 21, 11, 12, 19, 68, 56, 43, 23, 25, 39, 66, 42, 16, 47, 51, 8, 62, 14, 33, 24, 32, 17, 54, 29, 67, 49, 65, 35, 38, 59, 64, 28, 60, 0	<u>Used to allocate tiles to subchannels</u>
Nsubchannels	70	=
<u>Nsubcarriers</u> <u>Ntiles</u>	48 <u>420</u>	=
<u>Ntiles</u> <u>Number of subcarriers per tile</u>	420 <u>4</u>	<u>Number of all subcarriers used within tile</u>
Tiles per subchannel	6	=