

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Band-AMC operation in normal DL/UL-MAP	
Date Submitted	2005-01-24	
Source(s)	Jiho Jang, Jeong-Heon Kim, Seungjoo Maeng, Jaeho Jeon	jiho.jang@samsung.com
	<p>Samsung Electronics Co., Ltd. Dong Suwon P.O.Box 105 416, Maetan-3dong, Yeongtong-gu, Suwon-city, Gyeonggi-do, Korea 442-600</p>	
Re:	IEEE P802.16d-2004	
Abstract	Band-AMC operation and CQI report mechanism for the band-AMC using normal DL/UL-MAP are proposed	
Purpose	Adopting of proposed method into P802.16d-2004	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	<p>The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) <http://ieee802.org/16/ipr/patents/policy.html>, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."</p> <p>Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <mailto:r.b.marks@ieee.org> as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site <http://ieee802.org/16/ipr/patents/notices>.</p>	

Band AMC operation in normal DL/UL-MAP

1. Introduction

The adjacent-subcarrier permutation defined in 8.4.6.3 has benefits for AAS and band-AMC operations. The CQI feedback mechanism for the band-AMC operation when using H-ARQ MAP is well defined in the current standard. However, when the normal DL-MAP is used for band-AMC, the CQI feedback mechanism is not clear.

In this contribution, band-AMC operation and CQI feedback mechanism for the band-AMC in the normal DL/UL-MAP are proposed.

2. Suggested Text Changes

8.4.5.4 UL-MAP IE format

[Modify table 285 as follows]

Table 285 – OFDMA UL-MAP IE format

Syntax	Size	Notes
UL-MAP_IE() {		
CID	16 bits	
UIUC	4 bits	
if (UIUC == 12) {		
OFDMA Symbol offset	8 bits	
Subchannel offset	7 bits	
No. OFDMA Symbols	7 bits	
No. Subchannels	7 bits	
Ranging Method	2 bits	0b00 - Initial Ranging over two symbols 0b01 - Initial Ranging over four symbols 0b10 - BW Request/Periodic Ranging over one symbol 0b11 - BW Request/Periodic Ranging over three symbols
Dedicated ranging indicator	1 bit	0: the OFDMA region and Ranging Method defined are used for the purpose of normal ranging 1: the OFDMA region and Ranging Method defined are used for the purpose of ranging using dedicated CDMA code assigned in the MOBPAAG-ADV message.
} else if (UIUC == 13) {		
PAPR_Reduction_and_Safety_Zone_Allocation_IE	32 bits	
} else if (UIUC == 14) {		
CDMA_Allocation_IE()	32 bits	
else if (UIUC == 15) {		
Extended UIUC dependent IE	<i>variable</i>	See clauses following 8.4.5.4.3
} else {		

Duration	10 bits	In OFDMA slots (see 8.4.3.1)
Repetition coding indication	2 bits	0b00 - No repetition coding 0b01 - Repetition coding of 2 used 0b10 - Repetition coding of 4 used 0b11 - Repetition coding of 6 used
if (AAS or AMC UL Zone){		AAS/AMC Allocations include absolute slot offset.
Slot offset	12 bits	Offset from start of the AAS or AMC zone for this allocation, specified in slots.
}		
}		
Padding nibble, if needed	4 bits	Completing to nearest byte, shall be set to 0.
}		

8.4.6.3 Optional permutations for AAS and AMC subchannels

[At the end of this section, modify the following text as indicated:]

In the region mapped according to H-ARQ MAP in section 6.3.2.3.43, there are four types of AMC subchannels which are different in the collection of 6 bins in a band. In the first type (default type), the available bins in a band are enumerated by starting from the lowest bin in the first symbol to the last bin in the symbol and then going to the lowest bin in the next symbol and so on. A subchannel consists of 6 consecutive bins in this enumeration. The second type is 2 bins by 3 symbols, the third type is 3 bins by 2 symbols and the last type is 1 bin by 6 symbols. In the last three types, enumeration of bins in a subchannel is the same as in the first type. In all the types, the index of the subchannels in a band is increased along bins and then symbols.

In the region mapped according to normal DL/UL-MAP in section 8.4.5.3 and 8.4.5.4, there is only one type of AMC subchannel which consists of 2 bins by 3 symbols.

In all the types, data mapping follows section 8.4.3.4 except for region mapped according to section 6.3.2.3.43. Slots for downlink AMC zone in a region mapped according to section 6.3.2.3.43 are allocated along the subchannel index first within a band. The direction of data mapping for downlink AMC slots shall be frequency first (across bands when multiple bands are allocated).

Slots for uplink AMC zone in a region mapped according to section 6.3.2.3.43 are allocated along the symbol index first within a band. The direction of data mapping for uplink AMC slots shall be frequency first (across bands when multiple bands are allocated).

[Insert the following section 8.4.6.3.1 as follows]

8.4.6.3.1 Band-AMC operation in normal DL/UL-MAP

This section describes the band-AMC operation, which is designed for band-AMC enabled SS using normal DL/UL-MAP. The SS sends the REP-RSP message in an unsolicited fashion to BS to trigger Band AMC operation. The triggering conditions are given by TLV encodings in UCD messages. The REP-RSP (see 11.12 for the TLV encodings) includes the CINR measurements of five best bands. The band definition is in table 90, and the Max Logical Bands is set as '10' (12 bands).

For FFT sizes of 2048 and 1024, the number of Max Logical Bands is defined as 12. For FFT sizes of 512 and 128, the number of Max Logical Bands is the same as the number of physical AMC bands defined in 8.4.6.3. A logical band is a grouping of the physical AMC bands. For example, 12 logical bands for 1024-FFT imply that logical band 0 is composed of AMC bands (0,1), logical band 1 is composed of AMC bands (2,3), and logical band 2 is composed of AMC bands (4,5). In general, if $K = \text{Max Logical Bands}$, then logical band $J = [0..(K-1)]$ contains physical bands $M / K \cdot J, M / K \cdot J + 1, M / K \cdot J + 2, \dots, M / K \cdot (J + 1) - 1$ where M is the number of physical AMC bands.

The BS acknowledges the trigger by allocating Band AMC subchannels. From the next frame when the SS sent the REP-RSP, the SS starts reporting the differential of CINR five selected bands (increment: 1 and decrement: 0 with a step of 1 dB) on its allocated fast feedback channel (COICH). If the BS does not allocate the Band AMC subchannels within the specified delay (COICH Band AMC Transition Delay) in the UCD message, the SS reports the updated average CINR for the allocation of subchannel with

distributed subcarrier permutation.

When the BS wants to trigger the transition to Band AMC mode or update the CINR reports, it sends the REP-REQ message (see 11.11 for the TLV encodings). When the SS receives the message, it replies with REP-RSP. When the BS receives the REP-RSP, it should synchronize the selection of bands reported and their CINR. Unless the BS allocates subchannels with distributed subcarrier permutation, the SS reports the differential increment/decrement compared to the most up-to-date report from the next CQI reporting frame.